



50 V / 100 V combined transformer:

Primary connection:  
 5 (White) : 6 (Green) 50V  
 5 (White) : 8 (Red) 100 V

Secondary nominal tapings:

1 : 4	6,0 W
1 : 3	3,0 W
2 : 4	2,0 W
1 : 2	1,5 W
3 : 4	0,9 W
2 : 3	0,5 W

1W/1m Pink Noise 1/3 octave bands



Material / Colour..... Aluminium / RAL9010 or RAL3000  
 Mounting ..... 4 screws  
 Termination ..... Inside screw terminal  
 Weight ..... 1,5 kg  
 IP-rating ..... 56  
 Max. / min. amb. temp ..... 150°C / -40°C  
 Standard version ..... 100 V / 50 V transformer  
 Rated / max. power ..... 6 W / 10 W  
 SPL 1W/1m..... 87 dB  
 SPL rated power ..... 95 dB  
 Effective freq. range ..... 190 – 20000 Hz  
 Dispersion (-6dB) 1kHz / 4kHz ..... 160° / 90°  
 Directivity factor, Q.....

## Installation, Operation and Maintenance Procedures

- Open the cabinet by using the enclosed Allen key to loosen the three screws on 3 sides of the cabinet. Screw the loudspeaker with 4 screws to the wall or ceiling.
- For optimum performance, always use the correct voltage / power and operate within the frequency limits as stated.
- Do not open loudspeaker when energized.
- Fasten the front cover with a torque of 1-2 Nm.
- This loudspeaker is supplied with a 2 year warranty against defective workmanship.

Most of our products are available in different colours, impedances and power ratings.

